

LA-UR-19-30689

Approved for public release; distribution is unlimited.

Title: The Carrington GMD project

Author(s): Mate, Adam

Intended for: Presentation

Issued: 2019-10-21

Disclaimer:

Los Alamos National Laboratory, an affirmative action/equal opportunity employer, is operated by Triad National Security, LLC for the National Nuclear Security Administration of U.S. Department of Energy under contract 89233218CNA000001. By approving this article, the publisher recognizes that the U.S. Government retains nonexclusive, royalty-free license to publish or reproduce the published form of this contribution, or to allow others to do so, for U.S. Government purposes. Los Alamos National Laboratory requests that the publisher identify this article as work performed under the auspices of the U.S. Department of Energy. Los Alamos National Laboratory strongly supports academic freedom and a researcher's right to publish; as an institution, however, the Laboratory does not endorse the viewpoint of a publication or guarantee its technical correctness.



Oregon State
University



INFORMATION SYSTEMS
& MODELING

The Carrington GMD project

Adam Mate
Ph.D. Candidate

Los Alamos NM
August 19, 2019

UNCLASSIFIED

Outline

- Introduction
- Motivation of research – GMD and HEMP events
- Modeling GMD/HEMP-E3 events
- Halloween Solar Storm simulation and results
- Ongoing work

UNCLASSIFIED

Introduction

The Carrington event:

- Richard Carrington (1826-1875), English amateur astronomer
- September 1859: largest geomagnetic storm on record
 - first observations of solar flares by Richard Carrington and Richard Hodgson
 - Carrington suspected solar-terrestrial connection -- influence upon the Earth
- storm caused strong auroral displays, failure of telegraph systems

UNCLASSIFIED

Motivation of research

Importance of electricity:

- high dependency in all areas of our life
- short-term outages: nuisance, discomfort
- long-term outages: severe (chaotic) consequences


Nation's electrical grid

- key component of the critical infrastructure
- under constant threats

UNCLASSIFIED

Geomagnetic Disturbances

- GMDs are caused by solar flares
 - charged and magnetized particles from the Sun, which may disrupt Earth's magnetic field
 - coronal mass ejections (CMEs) lead to the largest GMDs
 - co-rotating interaction region (CIR): a high speed solar wind originating from a coronal hole
- results in auroral currents (electrojets)
 - magnetic field induces voltage in transmission lines





<https://phys.org/news/2016-03-powerful-geomagnetic-storms-solar.html>

UNCLASSIFIED

High-Altitude Electromagnetic Pulses

- brief, high-frequency electromagnetic waves
- HEMPs are caused by nuclear weapon detonations
 - E1 and E2: nearly instantaneous, damage to electronic components and low/medium-voltage infrastructure
 - E3: low-frequency GICs in transmission lines and power transformers ➡ similar to solar flares
- potential to cause significant damage



M. K. Rivera et al., "EMP/GMD phase 0 report, a review of EMP hazard environments and impacts," Los Alamos National Laboratory, LA-UR-16-28380, Nov. 2016.

UNCLASSIFIED

Effect on Power Systems

- Geomagnetically Induced Currents – induced quasi-dc currents in conductive infrastructure – are a major threat
- GICs may lead to ...
 - voltage collapse as a result of increased reactive power consumptions
 - increase of transformer temperatures, overheating of power transformers
 - misoperation of protection devices due to harmonics
 - potential cascading collapse of the entire grid
- Goal: understanding and mitigating hazard ➡ **MODELING**

UNCLASSIFIED

Modeling GMD/HEMP-E3 events

Knowledge is required about ...

- power system characteristics
 - geographical location of substations
 - resistance of system components, characteristics of power transformers
- geomagnetic source fields
 - amplitude, frequency content, spatial characteristics
- Earth conductivity structure
 - modeling method, substation grounding resistance, influence on geoelectric fields

UNCLASSIFIED

Modeling GMD/HEMP-E3 events

Julia



PowerModels.jl




PowerModelsGMD.jl

- open-source
- high-performance
- just-in-time

- Julia/JuMP package
- steady-state power network optimization

- based on PowerModels.jl
 - analyzing the impact of GMD/HEMP-E3 events
 - fast and reliable results
- developed by LANL-ANSI***




<https://github.com/lanl-ansi/PowerModelsGMD.jl>

UNCLASSIFIED


GMD event simulation

RTS-GMLC-GIC

Reliability Test System of the Grid
Modernization Laboratory Consortium



<https://github.com/GridMod/RTS-GMLC>



"PowerModelsGMD: An Open-Source framework for analyzing the impact of geomagnetic disturbances and high-altitude electromagnetic pulse E3 impact on bulk transmission systems based on PowerModels.jl," presented at the Military Operations Research Society 87th Symposium, Colorado Springs, CO, 19-Jun-2019.

UNCLASSIFIED

Slide 10


GMD event simulation

Halloween Solar Storm

- largest ever recorded GMD event
- 10/29/2003 12:00am – 10/30/2003 11:50pm

3-D geophysical modeling technique by OSU:

- determine earth conductivity structure model
- maximum induced voltage: on line C21 - 53.63V (at 10/30 7:56pm)
- longest line not necessarily going to see the largest GICs



UNCLASSIFIED

AC-OPF results

General Information:

- machine: Intel(R) Core(TM) i7-8809G CPU @ 3.10GHz, 15.9 Gb memory
- simulation period: most intense 30 minutes (10/30 7:45 pm – 8:14 pm) in one-minute time intervals

Number of converged periods	30 out of 30
Total comp. time	11.4805 sec
Avg. comp. time	0.3826 sec / period
Avg. cost of operation	\$ 87360.49

UNCLASSIFIED

AC-OPF results

Caused Q losses:

- greatest loss on “branch ID-88”

Avg. Q_{loss}



77.66 MVar

Lowest Q_{loss}

63.05 MVar (TP-1)

Highest Q_{loss}

116.06 MVar (TP-12)





10/30 7:58 PM

UNCLASSIFIED

AC-OPF results

Transformer temperatures:

- Actual = Ambient + Top-oil + Hot spot





UNCLASSIFIED

AC-OPF results

Transformer temperatures:

- most critical transformers



UNCLASSIFIED

Slide 15

Ongoing work

Development of PowerModelsGMD.jl

- Current capabilities:
 - quasi-dc power flow and ac optimal power flow (decoupled and coupled)
 - ac minimum load-shed (MLS)
 - ac optimal transmission switching with load-shed (OTS-MLS)
- Working on:
 - multi-time-period extension of OTS-MLS, since observed GMDs show time-varying behavior => mitigating transformer overheating

UNCLASSIFIED

Ongoing work

AC power flow equations

$$\sum_{e_{ij} \in E_i^+} p_{ij}^t - \sum_{e_{jt} \in E_i^-} p_{ij}^t = \sum_{g \in G_i} p_g^t - p_i^t - (V_i^t)^2 g_i \quad \forall i \in N^a, t \in T^a$$

$$\sum_{e_{ij} \in E_i^+} (q_{ij}^t + \lambda_e^t) - \sum_{e_{jt} \in E_i^-} q_{ij}^t = \sum_{g \in G_i} q_g^t - q_i^t + (V_i^t)^2 b_i \quad \forall i \in N^a, t \in T^a$$

$$p_{ij}^t = z_e (g_e (V_i^t)^2 - V_i^t V_j^t g_e \cos(\theta_i^t - \theta_j^t) - V_i^t V_j^t b_e \sin(\theta_i^t - \theta_j^t)) \quad \forall e_{ij} \in E^a, t \in T^a$$

$$q_{ij}^t = z_e \left(-(b_e + \frac{c_e}{2}) (V_i^t)^2 + V_i^t V_j^t b_e \cos(\theta_i^t - \theta_j^t) - V_i^t V_j^t g_e \sin(\theta_i^t - \theta_j^t) \right) \quad \forall e_{ij} \in E^a, t \in T^a$$

$$p_{ji}^t = z_e (g_e (V_j^t)^2 - V_i^t V_j^t g_e \cos(\theta_j^t - \theta_i^t) - V_i^t V_j^t b_e \sin(\theta_j^t - \theta_i^t)) \quad \forall e_{ij} \in E^a, t \in T^a$$

$$q_{ji}^t = z_e \left(-(b_e + \frac{c_e}{2}) (V_j^t)^2 + V_i^t V_j^t b_e \cos(\theta_j^t - \theta_i^t) - V_i^t V_j^t g_e \sin(\theta_j^t - \theta_i^t) \right) \quad \forall e_{ij} \in E^a, t \in T^a$$

Operational limit constraints

$$(p_{ij}^t)^2 + (q_{ij}^t)^2 \leq z_e s_e^2, \quad (p_{ji}^t)^2 + (q_{ji}^t)^2 \leq z_e s_e^2 \quad \forall e_{ij} \in E^a, t \in T^a$$

$$\underline{v}_i \leq v_i^t \leq \bar{v}_i \quad \forall i \in N^a, t \in T^a$$

$$|\theta_i^t - \theta_j^t| \leq z_e \bar{\theta} + (1 - z_e) \theta^M \quad \forall e_{ij} \in E^a, t \in T^a$$

$$z_g \underline{p}_g \leq p_g^t \leq z_g \bar{p}_g \quad \forall g \in G, t \in T^a$$

$$z_g \underline{q}_g \leq q_g^t \leq z_g \bar{q}_g \quad \forall g \in G, t \in T^a$$

$$z_g^t = z_g^{t-1} + y_g^t - \zeta_g^t \quad \forall g \in G, t \in T^a \setminus \{0\}$$

$$y_g^t + \zeta_g^t \leq 1 \quad \forall g \in G, t \in T^a$$

$$\sum_{\rho \in \beta_g} y_g^\rho \leq z_g^t \quad \forall g \in G, t \in T^a$$

$$\sum_{\rho \in \xi_g} z_g^\rho \leq 1 - z_g^t \quad \forall g \in G, t \in T^a$$

$$\bar{\gamma}_g \geq p_g^t - p_g^{t-1} - \bar{p}_g y_g^t \quad \forall g \in G, t \in T \setminus \{0\}$$

$$\underline{\gamma}_g \geq p_g^{t-1} - p_g^t - \bar{p}_g z_g^t \quad \forall g \in G, t \in T \setminus \{0\}$$

$$0 \leq p_i^t \leq \bar{p}_i^t \quad 0 \leq q_i^t \leq \bar{q}_i^t \quad \forall i \in N, t \in T^a$$

GIC effects on transformers

$$\sum_{e \in E_i^+} I_e^t - \sum_{e \in E_i^-} I_e^t = a_i V_i^d \quad \forall i \in N^d$$

$$I_e^t = z_e a_e (V_i^t - V_j^t + J_e^t) \quad \forall e_{ij} \in \mathcal{E}^d, t \in T^d$$

$$\tilde{I}_e^t \geq \begin{cases} I_{eH}^t & \text{if } e \in E^\Delta \\ \frac{\alpha_e I_{eH}^t + I_{eL}^t}{\alpha_e} & \text{if } e \in E^y \\ \frac{\alpha_e I_{eS}^t + I_{eC}^t}{\alpha_e + 1} & \text{if } e \in E^\infty \\ 0 & \text{otherwise} \end{cases} \quad \tilde{I}_e^t \geq - \begin{cases} I_{eH}^t & \text{if } e \in E^\Delta \\ \frac{\alpha_e I_{eH}^t + I_{eL}^t}{\alpha_e} & \text{if } e \in E^y \\ \frac{\alpha_e I_{eS}^t + I_{eC}^t}{\alpha_e + 1} & \text{if } e \in E^\infty \\ 0 & \text{otherwise} \end{cases} \quad \forall e \in E^a, t \in T^a$$

$$0 \leq \tilde{I}_e^d \leq \bar{I}_e^d \quad \forall e \in \mathcal{E}^r$$

Eqs. (5), (6)

$$\delta_e^t + \eta_e^t \leq \mathcal{T}_e \quad \forall e \in E^\Delta \cup E^y \cup E^\infty, t \in T^a$$

$$\lambda_e^t = k_e V_i^t \tilde{I}_e^t \quad \forall e_{ij} \in E^a, t \in T^a$$

$$z_e, z_g, y_g, \zeta_g \in \{0, 1\} \quad \forall e \in \mathcal{E}^a, g \in G$$

Supporting Constraints

$$z_g \leq \sum_{e \in E_i^+ \cup E_i^-} z_e \quad \forall i \in N_i^a, g \in G_i$$

$$z_g \psi_g^t \geq \kappa_g^2 (p_g^t)^2 \quad \forall g \in G, t \in T^a$$

$$\tilde{I}_e^t \leq z_e \bar{I}_e^d \quad \forall e \in E^a, t \in T^a$$

UNCLASSIFIED

Slide 17



THANK YOU!

UNCLASSIFIED